






## 3-3/4 digits 3999 Counts Pocket Sized True RMS Auto Range Multimeter

Item: MT-1506

**Large LCD, easy read**

**Relative value Measurement** 

**Full functions**

-  DCV
-  ACV true RMS
-  Resistance
-  Frequency
-  Capacitance
-  Diode test
-  Duty Cycle
-  Continuity with beeper
-  Continuity check



**Built-in test lead**



SIZE : 124 × 80 × 20 mm

DCV	400mV,4/40/400V ±(0.5%+4d), 600V ±(1%+4d)
ACV	400mV±(1.5%+6d), 4/40/400V ±(0.8%+6d), 600V ±(1.0%+6d)
Resistance	400Ω ±(0.8%+5d) 4k/40k/400k/4MΩ ±(0.8%+4d), 40MΩ ±(1.2%+5d)
Frequency	100/1000Hz/10k/100k/1MHz/10MHz ±(0.5%+4d)
Capacitance	4nF ±(5%+40d), 40n/400n/4μ/40μ ±(3.5%+8d), 2000μF ±(5%+8d)
Duty cycle	0.1~99.9% ±(0.5%+4d)
Continuity with beeper	50 ±30Ω
Diode test	Range: 0 ~ 1.5V Resolution: 1mV
Power source	2 x 1.5V AAA battery (Not included)
Size	4.9 x 3.1 x 0.8 in.

**Order Today! [SalesSupport@EclipseTools.com](mailto:SalesSupport@EclipseTools.com)**

Eclipse Enterprises, Inc. • Tel: 804.561.2610 • Fax: 804.561.2642

13302 Chula Road, Amelia Court House, VA 23002 • [EclipseTools.com](http://EclipseTools.com)